
Langie

TRANSLATOR LEARNING TOOL



USER GUIDE



** Insert the USB Power Adaptor into this port to supply power to your Translator or charge the batterv

STRAP HANGING HOLE

CHARGE THE BATTERY

** Before using the Langie for the first time or when the battery is low, you must charge the battery.

Fully charge the battery up to about 4 hours for first time use

** Use the USB Power Adaptor that comes with your device, connect your device to a power outlet.

The power plug of the adapter varies with your country of origin.

Input Voltage: 100V -- 240VAC Output Voltage: 5.0V.

** If the battery is completely discharged, you cannot turn on the device, even while it is charging

Allow the battery to charge for a few minutes before you try to turn on the device

INDEX

The Translator Layout.

Charae the battery.

Turning On and Home Screen.....

Features

Languages.

Specification.

Getting Started.

Status Screen..

Wi-Fi On/Off.

Voice Speed

Sleep Mode

Time Zone.

Alarm.

Hotspot..

Backup, Transfer,

Airplane Mode.

Cellular Data..

About Lanaie.

Multimedia

Favorites..

Dictionary.

Listenina.

FM Radio

Phone

Sound Amplifier

Voice Recorde

Group Interpreter

Language Club.

Troubleshooting.

message

using your translator

between charges.

Specification

Model: \$2

Memory: 16GB

continuous use

Wi-Fi: 802.11b/g/n

Earphone Jack 3.5mm

Input 100 V - 240 VAC

output: 5 VDC 1500 mA

Weight: 125 g (main body)

MSD Card : MicroSD Card

3G: WCDMA

(up to 32 GB)

USB Adaptor :

Update the Langie.

Voice Translator

Offline Translator.

Voice Search Images.

Offline Learning Flashcards ..

Offline Learning Phrases

Hotspot.Clock and Alarm..

Lanaie Global SIM Card.

** When the battery is low, the

device will show a low battery

Recharge the battery to continue

** When you are not using your

device, switch to Sleep Mode by

pressing the Power key. This can

help you to save battery power

and can use the device longer

CPU: Cortex 1.3 GHz QUAD-core

LCD: TFT 1.08 inch (27.5 mm)

- Standby : Up to about 5 days

- Translator: Up to about 5 hours

Charging Time: About 2 hours of

charging (about 4 hours with power on)

Dimension: W 48 x H 148 x D 17 mm

Battery : 3.7 V / 2000 mAh

Product: Langie Translator

Brightness.

History...

Setting the devices

Translator Language

System Language

Langie TRANSLATOR . LEARNING TOOL USER GUIDE

A direct voice delivery translator that instantly translates your words. as if you are direct communicating with other person.

FEATURES

. 10

10

10

.13

1.3

.13

13

. 13

.14

.14

14

.14

.15

15

1.5

18

19

20

20

21

. 21

.22

22

. 22

.23

.26

27

.28

..28



VOICE TRANSLATOR voice and Translate to

Recognize vous large amount of languages. The online voice translator will more accurately identify what you say and hear. Internet connection needed.



SEARCH IMAGES

Recognize vour voice and Search large amount of images for your reference. A suitable picture can help you to easily communicate with people. Internet connection needed.

GROUP INTERPRETER distance) languages

two languages.

interpreter

USA

(no limitation of Connect group conversation with people in various Specially designed seminars or tourist quide business

for meetings.

LANGUAGE CLUB

Meet friends and

learn a new

FAVORITE

HISTORY

Save your

* Prepare and

translation during

you to use and

translation even

you are on the

status without

** Keep your

conversation

history.

internet translation

review those

online mode, help

language and

culture in Langie

Language Club.

* Connect two Langie Translators

to get a private conversation in

* Connect multi Langie Translators

as if each person has an own

* Internet connection needed.

Have a conversation with a native

language classmate, share

translation or dictionary.

to talk with various language users

TRANSLATOR Recognize vour voice of short phrases or simple words, built in algorithm to aenerate an understandable translation. NO internet needed.

OFFLINE



A learning drill for language basic. Built in phrases and flashcards with image and voice tap to bear from ABC to basic vocabulary or phrases NO internet needed.



MULTIMEDIA Gallery, Radio Video and Music



VOICE RECORDER SOUND AMPLIFIER

GETTING STARTED

Turning ON and HOME Screen

1]. Press and hold the power button for about 5 seconds until you see the display turning On to Home Page



21. The Home Page is the Voice Translator and shows two languages The language on top is the speaking language, the language on bottom is the translation language

3). This feature requires to connec-

internet 41. When it is connected with

Wi-Fi, the Wi-Fi ico lights ON on the left side

51. When it is the 3G icon.

connected with 3G. lights ON on the right side.

Status Screen

** The battery indicator is showing the percentage of battery power status. ** Once you insert a SIM card, the internet indicator is light ON and show the local telecommunication company showing ON. name

** When Wi-Fi is connected, the Wi-Fi indicator lights on blue and show the AP address name, otherwise it is

2

If there is none of AP address name below the Wi-Fi indicator, go to Settings mode to search and connect the Wi-Fi again

Setting the device



** Swipe to Settings screen to set up your device. Scroll up and down to select the item

1]. SYSTEM LANGUAGE

Scroll down to Menu bar and tap the System, select and tap your of this device, e.g. English.



2]. WI-FI On/Off

** By default, your Langle activates the Wi-Fi feature. We suggest you to activate the Wi-Fi feature at any time which you can feel much better performance of the unit. If you want to turn off the Wi-Fi, just simply tap the block

** Please note, if the Wi-Fi AP just show 'Saved', it is not connected and you have to connect again. ** If the password is wrong, you can anguage to be the System language hold the Wi-Fi name, then tap 'forget'

** Scroll to Wi-Fi bar and tap it. It

Tap the name and connect to a

[OK] to confirm and [Connect] to

access the internet

searches and displays the available

Wi-Fi AP, the LCD displays a keyboard

and you may type the password, tap

** Once the Wi-Fi is successfully connected, swipe to the Status Screen and you can see the Wi-Fi indicator is On with the AP name, e.g.



(It is not connected if there is none of AP address name below the Wi-Fi icon)

_ VOLUME ** Press the Volume key (+)

other said.

DUAL SPEAKER SYSTEM

The Langie is equipped with

built-in high quality dual

Speakers, one on the rear

that the other people can

hear clearly what you said.

One on the front that you

can hear clearly what the

THE TRANSLATOR LAYOUT

to louder, (-) to lower ** It displays a volume dialog box to indicate the volume level.

POWER BUTTON ON/OFF ** Turn ON

Press and hold the power button for about 5 seconds until you see the display turning On

** Turn OFF -- Press and hold the power button for about 3 seconds to display the shutdown dialog box, tap POWER OFF to shut down ** Press the power button for sleep mode (off the LCD) when not in use.



1. Nano SIM card

** The MSD card slot is inside the plastic cabinet. ** Insert a Micro SD Card into this

slot for other external memory extension up to 32GB.

3]. TRANSLATOR LANGUAGE

** Scroll up to the top line of Settings screen. tap the icon of Translator to select your Speaking Language (From) and Translation



box of (From) up/down to tap your language, e.a. Enalish



Afrikaans

Arabic

scroll to tap your translation language, e.g. Chinese ** Press the front speak key to go

home page, you can see the home page shows the languages English to Chinese.

** a microphone icon () == Speaking Language.

** a speaker cross icon (== Translation Language without audio.

FRONT LED

Lights on once you press the Front Speak Key.

FRONT SPEAK KEY

lanauaae

last screen or home screen from anywhere.



41 HISTORY ** Turn ON the history, the Lanaie can record what vou have translated that you can review Tap ENTER to see your translation history.

aet back to last

screen or home

screen from

anywhere

** Tap to set TRANSLATOR VOICE SPEED to normal or slow

61 BRIGHTNESS ** Brighten the

Langie LCD by taping(+) or (--) to dim it.

71 SLEEP MODE

** Tap Sleep Mode to set your unit to turn off LCD from 1 to 5 minutes when you are not using the unit.



81. BACKUP TRANSFER

(only available on some models) ** You may backup the Favorite and History translation for using those contents in your computer.

press 'YES' to confirm the backup

** You may make necessary translation amendment in your computer, transfer it to the Langie Favorite mode.

that to receive your voice, another on the rear that to receive other voice TOUCH SCREEN - LCD

Built-in high quality

dual Microphone,

one on the front

LANGUAGES

53 Speaking

Languages

Afrikaans

Arabic

Benga

Bulgariar

Cambodiar

Cantonese

Chinese

Croatian

Czech

Danish

Dutch

English

Filiping

Finnish

French

German

Greek

Hebrew

Hungaria

celandio

Indonesia

Japanese

Javanese

Korean

Latvian

Malay

Nepali

Persian

Polish

Portugu

Romaniar

Russian

Serbian Sinhala

Slovakiar

Slovenian

Spanish

Swahili

Swedish

Tamil

Teluau

Turkish

Vietnamese

Ukrainian

Urdu

Thai

Sundanes

Lithuanian

Malavalar

Norwegiar

Lao

Italian

Hindi

Langle has large amount of languages, the language quantity and

Translator Audio Phonetic

H(())

(d) 0

B(0)

((0)

■(0)

H(0)

1(0)

(0)

(40

B(())

ndo)

((0)

H(b)

mate)

noted: The languages and data are being continued to add and improve.

The updated are pushed over the air (OTA), directly to your Langie device.

6

therefore, other than the above listed specification, you may find more

■(0)

0 **■**(0) 0

Words

0

0

0 0 0

•

0 0

0

0

0 0

0 0

0

0 0 0

0 0

0

0

0

0

0

0

0

0

0

0

0

combination depends on different models. Language List -->

0

0

Online Translato

Swipe left/right up/down or Tap to use an application

** Press and Hold it to speak your

** Simply press it to get back to



51 VOICE SPEED



** Tap to enter the BACKUP screen.

13

Tap to enter TRANSFER screen,

press 'YES' to confirm the transfer to Langie

languages or audio in future in your device.

** If there is file more than one, only the latest file can be transferred to the Langie



You can add more storage by inserting the msd card to save the file.

10 11 12



101. TIME ZONE Set your time zone for Clock or Alarm.





11]. ALARM Tap "Add Alarm" to turn on Alarm or save the Alarm time



12]. CELLULAR DATA

3G provides internet cellular data which consume your SIM card value, suggest you to turn ON only for Voice Translator

For the Group Interpreter or Language Club, use it only with Wi-Fi connection.





14

You may use the Langle Phone to dial emergency call in a local city. ** If you insert a SIM card with telephone number, you can use Langie Phone same as a usual phone. To dial and receive. Meanwhile, you may receive or send SMS message.

SMS support the characters include the Latin alphabet, numbers and other symbols found on the keyboard

HOTSPOT

** If you are using ভূ a large data SIM card, you may share the Lanaie Wifi Hotspot to your other devices. Tap the screen to turn Hotspot ON.

You may change your name and password if needed. CLOCK AND ALARM

** Tap 'add alarm to turn ON alarm. and set the alarm time.

Group Interpreter (Wi-Fi or 3G needed) (no limitation of distance)

** We suggest you to put on an ear phone to have private conversation with your group.

** Swipe right from Home page to the screen of Group Interpreter



17:32

** Input your name on user column and select your speaking language, e.g. Tom, English,

23

** Tap OK to confirm

1.31 PHONE SETTINGS

14]. HOTSPOT

15]. ABOUT LANGIE

Voice Translator

of Languages)

e.a.

(Wi-Fi or 3G needed)

** Tap to enter to see it's versions

Recognize your voice and Translate

to large amount of languages.

identify what you say and hear.

(See the Language List on page

the language on top is the speaking

language, the language on bottom

Tap 'Create Group' and type a group

and you can share this code to invite

Tokyo Tours

Tokyo Tours Code : 10632

name. Langie will generate a code

connection, it will more accurately

This feature requires internet

On the Langie Home Page.

is the translation language.

English to Chinese

Create Group

participant

Group Code 10632

Join Group

Type group name or code to

search, and send request

Group Information

in the Group

Tap : to Group Information to

Lock/Remove/Transfer ownership

see Participants, History or to



A 1234567

Once you see the Speaking icon (((O))) shown on LCD and hear a beep sound, you may speak with you language, e.g. (Why communication is so Important?)

** While finishing with voice messaging, release the speak key to have translation instantly

21. Langie delivers the voice and displays the translation at the 什么沟通如此重 same time, if the other cannot hear the voice clearly. you can tap the LCD translation and Lanaie will repeat to speak.

31. Scroll up and down to see the whole display with bigger words or roman phonetic. Tap the screen to hear the slow speed voice.



5什么沟通如此 要

51. Press the front Speak key to speak new words o phrases. 16

name can remove or transfer

Transfer the ownership.

ownership.

Group Chats ** Press and Hold the Front Speak Key to speak and chat, e.a. (where are you from)

** Only owner can Lock/Remove/

** In Group Info, hold the participant

** The Langie will translate your words and send voice translation to the other connecting device. Your friend can hear and see with his language (你是哪国人?) Ní shì nă quó rén?) on his device what you said, you can hear and see with your language on your





LANGUAGE CLUB You may meet friends and learn a

new language and culture in Langie Lanauaae Club. Have a conversation with a native language club mate, practice the language listening and speaking.

17 ** You are one of the club member with your Langie device.

USA

On the top of screen, vou may see your membe number ** Type your

Rear Speak key --

11. PRESS and HOLD

top of the Rear key

the back Speak key,

other language

the blue LED on

2]. Once hear a

beep sound, the

other can speak

her/his language

e.g. she speaks

(沟通驱使着我们

的生活改善自己)

you at the same time.

LCD translation screen

Voice Search Images

(Wi-Fi or 3G needed)

Recognize your voice

and Search large

amount of images

for your reference

** Swipe to the

Images

screen of Search

3]. Langie translates with your

language, speaks and displays to

if you like to hear it again, tap the

to you with

Chinese

will light on.

name, select your place to sign in. ** Tap to enter the language club you want to learn that



** Search your club mate and send your request.



** Hold the blue speak key to speak and send. Your club mate may speak and respond to you with her/his language

** You can press edit to add or remove the club.

** Confirm with your language arade level that it is easier to search right club mate fo vour taraet lanauaae.

18 Langie Global SIM Card (optional) Only available to those models

contain the Langie Global SIM Card. * The SIM card is installed into the card slot ** It contains about 50MB that you can use over 500 translation or few months in most of countries in

11. PRESS and HOLD

the Front Speak key,

speak the word of

Your language is to

follow the settings

language (From)

first few images

pictures.

Multimedia

Music Player.

Copy your files

through USB cable

or insert MSD card

icon to enter into

Tap to enter to

see the translation

** Swipe Left or Right

to see previous or

next record.

** Tap ••• to

delete the record.

record you have

it's function.

Favorite

saved

and tap the feature

沟通驱使着我们 约生活改善自己

e.g. London Big Ben

2]. Langie displays your words, starts

search from internet and shows you

Speak key, speak the word of other

language to search pictures. The

settings of translator language (To).

Contains Gallery, Radio, Video and

other language is to follow the

Scroll up and down to view the

31. PRESS and HOLD the Rear

your language.

of translator

world. ** The SIM card is valid of years. After the data used up, you may top up the SIM from www.langieglobalsim.com ** The Langie Global SIM Card is

installed together with the Langie device, the Card is not sold

** To see your balance value. go to Settings, Langie SIM ->



UPDATE THE LANGIE The Langle is continuous to

provide upgrade version on server for any data or feature improvements. You may update your Langie once the LCD shows APP update, tap update to download and estart vour unit. If you want to check a update version, turn off your Langle then turn it ON and connect Wifi again the APP update icon will appear

on your LCD in few minutes to ask

for update or not.

TROUBLESHOOTING How to increase accurac of voice recognition and translation?

Offline Translator

Recognize your voice of short

built in algorithm to generate an

down the language list to select

languages. Top language is the

Bottom language is the Translation

Front Speak key to speak your words

Rear Speak key to speak the other

4]. Translation is displayed on LCD,

you may tap LCD to hear again.

(noted: We suggest you to use

Online Translator which you can

get much better performance.

When you use Offline Translator,

words and give a translation.)

5]. Scroll Up and

Down to see the

whole display of

or Roman phonetic

biager words

please speak slow, clear, simple and

correct grammar phrase that can

help the translator to recognizeyou

十么沟通如此

phrases or simple words.

No internet needed.

** Swipe to the

Translator.

language.

or phrases

lanauaae.

screen of Offline

1]. Tap (🔻) to pull

Speaking language;

21. PRESS and HOLD the

3). PRESS and HOLD the

understandable translation

a) Connect your device to the internet via wifi or share hotspot from cell phone.

19

b) Try to speak closer to the microphone.

c) Try to speak louder and clearer

d) Try to use fluent and structured sentence when speak.

2. What else may affect the Offline translation accuracy of Langie?

 a) Noisy environment b) Different accent

Too long or too short phrases

* Online Translator can work in noisy environment if the Wi-Fi or 3G connection is stable.

3. How to connect to wifi after typing password without an "ENTER" key on the keyboard? Tap "OK" key on keyboard afte typing and press "CONNECT"

4) Why I cannot connect to internet even the wifi name shown as "SAVED"? Saved network only represents it is not a new network but it does not mean LANGIE has already connected to the network. Press the network name and connect again.

5. How to do when I fail to connect to "SAVED" network? Press and hold the network name choose "FORGET". Press the network name again and enter password

6. Does Langie still work even without internet connection? Yes. Offline functions as below

a) Limited language translation (Refer to Manual)

Offline Learning Flashcards

A learning drill for language basic There are about 200 flashcards in 13 categories at each language 11. Tap one of the

** Select your learning language.

ords 2 English • 11. Tap one of the category icon to ОК enter e.g. Numbers

2]. Tap the picture to hear the voice.

3]. Scroll up and down to see the next picture in same category

** 13 Categories --> Alphabets, Numbers, Clock, Month, Week, Vegetables Fruits Food Shapes Sports, Music, Horoscope and Chinese Zodiac

Offline Learning Phrases

** Select your language and you target learning language, tap OK to confirm.

20

b) Offline translation accuracy at

Why even my Langie has

accuracy at 90-100%

run as usual

40-50% while Online translation.

c) Learning functions and Multimedia

connected to internet, there is

still a pop up message showing

Langie processes translation via

be able to access the bia data.

country if the country controls its

own internet controlling system.

8) What are the techniques in using

a) Do not release your finger when

b) Start to speak only after you hear

immediately after you speak.

hold the speak button for awhile

does not come in audio but text

after language switch as it takes

some time to reload database.

If there is a "MUTE" icon next to a

translation of that language is not

available Translated content will

only be displayed in text instead of

language, it means the audio

audio of translated content?

audio of translated content

Tap the screen to repeat playing

b) The audio translation may not be

available of that particular

10) What is the meaning of the "MUTE" icon shown next to a

11) How to repeat playing the

the sound signal when you press

You may try it again

the speak button?

you are speaking

the speak button

only?

language.

language?

c) Do not release your finger

9) Why the translated content

a) Langie may experience a delay

from the cloud server outside this

that the internet is not available?

cloud server, sometimes it may not

11 Tan one of the category to enter. e.g. Making Friends

21 Tap the phrase to have it's translation, tap the screen to hear the voice

Would you like t ao out for dinner 夕食に出かけた いですか?

DICTIONARY

31. Or Type the word (no internet

dictionary to enter.

21. Speak the word

conection needed)

4]. e.g. discuss

Tap the target

words to hear the

6]. Hold and tap the

target words to share

it to your club mate

in Langie Language

or insert MSD card to listen

language to play.

Copy your text files through USB cable

Tap the file name to open the file.

Hold the screen to select the text

** The text file must copy to the

**The Text file format must be

12) What to do when the Langie

Press on/off key and don't

release it until you can see

but I am hard to follow the

voice, what's your suggestion?

go to setting -> voice speed,

to make easier to follow the

change the voice to "slow" speed

We also suggest you to turn ON

history or save the phrases in you

For a non-Roman language, you

may scroll up/down to see the

whole display which shows both

original characters and Roman

pronunciation. It will be easier for

you to listen the voice follow the

recognize my MicroSD card?

** MicroSD cannot be bigge

than 32GB, please check the

** MicroSD format is the FAT32,

card to FAT32 and try it again

will be saved in your MSD card ->

If you insert your MSD card, the file

will be saved in your MSD card ->

folder -> 'Backup'. Otherwise, the

Langie Internal folder -> Backup

file will be saved direct in the

folder -> 'MultimediaRecord'.

direct in the Langie Internal

16) Where of my file be saved in

folder -> MultimediaRecord'.

Otherwise, the file will be saved

memory size of your card.

if not, please format the

15) Where of my file is saved in

Recorder?

Backup?

Favorite record, review them and

13) I am a language learner

UTF-8 encoding format.

is hanged?

the LCD is off

You can

pronunciation.

hear several time.

Roman display.

14) Why the Langie cannot

folder "Listening" in Langie or MSD

21

voice.

Club.

Listening

It can help you to easier ** Built in large amount of dictionary

discuss

nop grs

[dis'kns]

communicate with a medium hearing loss people

Sound Amplifier

** Press and Hold the front 🗸 or rear speak key to speak

e.g.(we go out for dinner tonight).
** The Langie records your words and speak it loudly, LCD shows an amplifier icon

** If you want the other to hear the same words again, tap the amplifier icon to repeat it.

VOICE RECORDER

* Tap the red circle to start voice recording. ** Tap the list to



You can add more storage by inserting the msd card to save the

FM RADIO

** Must connect an earphone to have it to be an aerial.



** Tap the top right icon to select using speaker or earphone. ** Tap the left or right arrows to search FM frequency.

PHONE

**** If you insert a SIM card with data only, it provides only the internet data but not a telephone number



17) Why my Langie Global SIM cannot make a call? Please dial '00' + Country Code + Phone Number to call

18) Why I can't use Search Image even I already inserted SIM? Please go to setting -> cellulor data, to check whether the Search Image is ON.

19) Where can I set the APN in Langie? Please go to setting > Phone

Setting to create the APN. 20) How can I setup the TIME?

When Langie connected Wifi or Internet by inserting a SIM, it will update the time automatically. If Langie can't obtain the time correctly, you can go to setting -> Time Zone to set the time manually. If the Time still incorrect, please try to connect another WiFi to try again.

21) Why the Hotspot connected is lost automatically?

If Langie detected the connection was not used for a long time, the Hotspot will turn off automatically. If you need to use the connection again, you may go to Hotspot to turn it ON again

If you insert your MSD card, the file RoHS ✓ Ž FC 😭

SAR Notice (For Japan) Main module Reported (W/Ke)

26 30